



NOTICE

**THIS CASH DISPENSER
SUPPORTS**

CARDWAY COMMUNICATIONS!

IMPORTANT:

- PLEASE VERIFY CARDWAY SUPPORT IS PROVIDED BY YOUR ATM TRANSACTION PROCESSOR!***
- CARDWAY IS TURNED OFF BY DEFAULT! BE SURE TO TURN CARDWAY ON IF REQUIRED BY YOUR PROCESSOR!***

CARDWAY FEATURE SETUP

1. Press and hold the **BLUE** key on the ATM keypad. Press the **<1>** key. The Top-Level menu appears. Release both keys.
2. From the Top-Level menu, choose the following options in sequence to reach the Cardway configuration screens:
 - MANAGEMENT FUNCTIONS***
 - TERMINAL CONFIGURATION***
 - SET TERMINAL PARAMETERS***
 - TELEPHONE (To Enter CARDWAY Telephone Number)***
 - CARDWAY (To Turn CARDWAY ON/OFF and enter the NETWORK USER ADDRESS [NUA])***
3. See the reverse for coverage of telephone number and NUA entry procedures.

TELEPHONE NUMBER SETUP

The phone number is supplied by your *Processor*, and is required for ATM communications. When the phone number entry screen is reached, the current phone number (if any), will be displayed. What happens next depends upon the model-type of the *modem* installed in the terminal:

EXTERNAL 3COM® U.S. ROBOTICS MESSAGE MODEM

1. Press **CHANGE** to blank the current entry (if applicable) and enter the entry mode.
2. Enter the phone number. **DO NOT** enter dashes in the number!
3. Press **OK** to accept the number.

STANDARD INTERNAL MODEM

EXTERNAL 3COM® U.S. ROBOTICS COURIER

1. Press **CHANGE** to blank the current entry (if applicable) and enter the entry mode.
2. **Enter a carat (^) symbol.** To enter a carat symbol, press the **<BLUE>** key, then press the **<3>** key **FOUR** times.
3. Enter the phone number. **DO NOT** enter dashes in the number!
4. Press **OK** to accept the number.

***IMPORTANT: DO NOT ENTER A CARAT SYMBOL IN FRONT OF THE PHONE NUMBER IF YOUR PROCESSOR DOES NOT SUPPORT CARDWAY!**

CARDWAY CONFIGURATION

The Cardway screen enables you to turn the Cardway feature **ON** or **OFF**, and to enter the **Network User Address (NUA)**.

ON/OFF. You can see the current status of the Cardway feature in the caption of the leftmost menu option. To change the status, press the button next to this option. This will change the status to **ON** or **OFF**, as applicable.

NETWORK USER ADDRESS (NUA). The NUA is supplied by the *Processor*, and is required for access to the Cardway communications network. Select **CHANGE** to blank the current entry. Enter the NUA number and press **OK** to accept it.