

TECHNICAL BULLETIN: 14-15

DATE: October 8, 2014

SUBJECT: Hole Close Out Plate Kit for RL16XX, RL23XX, and RL5XXX.

AVAILABILITY: All Authorized Triton Distributors and Third Party Service Providers

This bulletin addresses:	
	Hardware Service Issues
X	New Kit/Parts Available
	Software Announcements
	Technical Tips

Recommended Implementation is:	
	Now for all affected units
	All affected units during next service visit
X	Optional but highly recommended
	No implementation required

DESCRIPTION:

Criminals and fraudsters continuously hone their craft in an effort to take advantage of your ATM investment. Triton and ATMGurus' engineering teams are constantly striving to improve security on our new and legacy ATMs in an effort to stay one step ahead of criminals who attack your ATMs. You should regularly upgrade the security of your ATM fleet just as you do with your company servers and computers. Besides updating to the Advanced Security Module as outlined in Technical Bulletin 13-29, the Hole Close Out Plate Kit, 06200-08211, should be added.

When visiting your ATM to upgrade for EMV or PCI, or to even load paper or currency, use the opportunity to ensure you are protecting your investment and revenue stream.



DESCRIPTION: Cont.

When adding the close-out kits, the cables also need to be rerouted. The number of kits required depends on the business hour cabinet or level one vault. Use the tables to determine the number of close out kits needed. The ARGO was designed to eliminate these risks and does not need these kits.

RL51X5—XScale– NMD Dispenser			
Cabinet or Vault	Cabinet or Vault Part Number	Serial Numbers	Number of Kits
Business Hour	09700-00000	LRL511503251xxxx - LRL511504295xxxx	1
Cabinet	09015-00052, 03015-00167	LRL511504296xxxx - LRL511507339xxxx	2
Level One Vault	03015-00064, 03015-00200, 03015-00227	LRL512503297xxxx - LRL512507378xxxx	2

RL53X5—X2 –NMD Dispenser			
Cabinet or Vault	Cabinet or Vault Part Number	Serial Numbers	Number of Kits
Business Hour	03015-00052, 03015-00167	LRL531507340xxxx - LRL531509314xxxx	2
Cabinet	03015-00793, 03015-00833, 3015-01340 03015-00852, 03015-00900	LRL531509315xxxx - LRL531514364xxxx Also need to purchase: 09120-07199 - NMD50 Power Cable 09120-00900 - SM power cable	2
Level One Vault	03015-00064, 03015-00200, 03015-00227	LRL532507352xxxx - LRL532509214xxxx	2
	03015-00798, 03015-00212, 03015-00841 03015-00851, 03015-01841	LRL532509215xxxx - LRL532514364xxxx	2



09120-07199
NMD50 Power Cable with Ground



09120-00900
Security Module Power Cable

RL51XX—XScale- TDM				
Cabinet or Vault	Cabinet or Vault Part Number	Dispenser	Serial Numbers	Number of Kits
Business Hour Cabinet	09700-00000	TDM100	LRL511103248xxxx - LRL511104298xxxx	1
		TDM150	LRL511203274xxxx - LRL511204285xxxx	1
	09015-00052, 03015-00167	TDM100	LRL511104299xxxx - LRL511107339xxxx	2
		TDM150	LRL511204309xxxx - LRL511207339xxxx	2
		TDM200	LRL511705157xxxx - LRL511707334xxxx Also need to purchase: 09125-00926 - TDM Harness	2
Level One Vault	03015-00064, 03015-00200 03015-00227	TDM250	LRL511805157xxxx - LRL511807334xxxx Also need to purchase: 09125-00926 - TDM Harness	2
		TDM100	LRL512104296xxxx - LRL512107316xxxx	2
		TDM150	LRL512205213xxxx - LRL512207295xxxx	2
		TDM200	LRL512706051xxxx - LRL512707192xxxx	2
		TDM250	LRL532807306xxxx - LRL532809314xxxx	2

RL53XX—X2- TDM250			
Cabinet or Vault	Cabinet or Vault Part Number	Serial Numbers	Number of Kits
Business Hour Cabinet	03015-00052, 03015-00167	LRL531807306xxxx - LRL531809314xxxx Also need to purchase: 09125-00926 - TDM Harness	2
	03015-00793, 03015-00833, 03015-01340 03015-00852, 03015-00900	LRL531809315xxxx - LRL531814364xxxx	2
Level One Vault	03015-00064, 03015-00200, 03015-00227	LRL532809215xxxx - LRL532814364xxxx	2
	03015-00798, 03015-00212, 03015-00841 03015-00851, 03015-01841	LRL532809215xxxx - LRL532814364xxxx	2



09125-00926 TDM Harness

RL51X4—XScale—SDD Dispenser

Cabinet or Vault	Cabinet or Vault Part Number	Serial Numbers	Number of Kits
Business Hour	09700-00000	LRL511403248xxxx - LRL511404295xxxx	1
Cabinet	09015-00052, 03015-00167	LRL511404296xxxx - LRL511407353xxxx	2
Level One Vault	03015-00064, 03015-00200, 03015-00227	LRL512403329xxxx - LRL512407353xxxx	2

RL53X4—X2—SDD Dispenser

Cabinet or Vault	Cabinet or Vault Part Number	Serial Numbers	Number of Kits
Business Hour	03015-00052, 03015-00167	LRL531407323xxxx - LRL531409297xxxx	2
Cabinet	03015-00793, 03015-00833, 03015-01340 03015-00852	LRL531409315xxxx - LRL531414364xxxx Also need to purchase: 09120-07199 - NMD50 Power Cable	2
Level One Vault	03015-00064, 03015-00200, 03015-00227	LRL532407352xxxx - LRL532409214xxxx	2
	03015-00798, 03015-00212, 03015-00841 03015-00851, 03015-01841	LRL532409215xxxx - LRL532414364xxxx	2

RL23XX—X2

Cabinet or Vault	Cabinet or Vault Part Number	Dispenser	Serial Numbers	Number of Kits
Deep	03015-00166, 03015-00790,	TDM250	LRL231808134xxxx - LRL231813225xxxx	2
Business Hour	03015-00804, 03015-00253,	SDD	LRL231407137xxxx - LRL231413331xxxx	2
Cabinet	03015-00848	NMD50	LRL231507134xxxx - LRL231513214xxxx	2
	03015-00862	MM	LRL231308221xxxx - LRL231313210xxxx	2
Level One	03015-00784, 03015-00792,	TDM250	LRL232807354xxxx - LRL232813150xxxx	2
Vault	03015-00798, 03015-00212,	SDD	LRL232407352xxxx - LRL232413196xxxx	2
	03015-00841, 03015-00851, 03015-01841	NMD50	LRL232407340xxxx - LRL232513200xxxx	2

CONFIDENTIAL

DESCRIPTION: Cont.

RL1600 does not need close out kits but the cables should be rerouted per instruction manual, 07103-08210. RL2313 built with shallow business hour cabinet, 03015-00148, does not need closeout kits but cables should be rerouted per instruction manual, 07103-08210. To reroute the cables in the shallow business hours cabinets, one Panduit Adhesive Cable Clip, 03072-00009, is needed.

RL16XX & RL23XX with MM in Shallow Business Hour Cabinet				
Model	Cabinet Part Number	Dispenser	Serial Numbers	Number of Kits
RL1613	03015-00799, 03015-00272 03015-00277	MM	LRL1613 08354 xxxx - LRL1613 14200 xxxx	0
RL23XX	03015-00148	MM	LRL2314 07242 xxxx - LRL2314 08220 xxxx	0



03072-00009

Panduit Adhesive Cable Clip

If you have questions regarding this Technical Bulletin, please contact Technical Support at 1-228-575-3100 or toll free in the U.S. / Canada 1-800-259-6672.

Visit www.Triton.com for additional information.

For all ATM Parts, Repair, and Training needs, visit www.atmgurus.com.