

TECHNICAL BULLETIN

SUBJECT:
CDM8240N DISPENSER FOR ARGO FT

TECHNICAL BULLETIN: 24-05
DATE: OCTOBER 15, 2024

Confidential - Available to all authorized Triton distributors and third party service providers

RELEASE OF THE CDM8240N DISPENSER FOR US AND CANADA X4 MAINBOARD SOFTWARE VERSION 5.1

Triton announces the release of the CDM8240N dispenser option for the ARGO FT. The customer can order either the NMD100 or CDM8240N dispenser in their new ATM. The CDM8240N dispenser option requires the X4 mainboard hardware, and terminal software version 5.1. X4 requires Triton Connect version 6.3. For fielded ARGO FT with NMD100 conversion to CDM8240N, contact sales@triton.com or 1-228-575-3100 opt (4).

****NOTE****

The CDM8240N requires a larger service area. Please review the updated ARGO FT Installation Manual with CDM8240N dimensions.



CDM8240N FEATURES:

	CDM8240N:
Number of Cassettes	2 or 3
Cassette Capacity	2800 ATM Fit Notes (15 in, 381 mm)
Reject Capacity	250 Notes
Security Features	Mechanical Key lock and Plastic Seal
Note Feeding Method	Friction
Note Dispensing Type	Bulk Dispensing
Dispensing Speed	7 - 8 notes per second
Maximum number of Notes Dispensed per Transaction	50 Notes
Notes Low	Select 50 ~ 250
Dispenser Weight, Long Presenter	2-cassettes: 77 lbs. (35 kg) 3-cassettes: 96 lbs. (44 kg)
Dimensions (H x W x D) 2-Note Cassettes, No Brackets	(H x W x D) 19.75 x 11.5 x 34.25 (Long Presenter) 19.75 x 11.5 x 28.375 (Short Presenter)
3-Note Cassettes, No Brackets	(H x W x D) 25.375 x 11.5 x 34.25 (Long Presenter) 25.375 x 11.5 x 28.375 (Short Presenter)
Communications	RS-232
Power Consumption	Static power consumption: 30W; dynamic power consumption: 140W.
Working Temperature and Relative Humidity	0°C ~ 50°C, 32 - 122°F 20% ~ 90% RH (without condensation)

If you have questions regarding this Technical Bulletin, please contact Technical Support at 1-228-575-3100, option 3 or toll free in the U.S. / Canada 1-866-259-6672, option 3. Visit www.triton.com for additional information. For all ATM parts, repair, and training needs, visit www.atmgurus.com.